





Type	Polarity	Application	Maximum ratings		Characteristics at 25°C								Case
			P _{tot} (mW)	V _{CEO} (V)	f _T / I _C typ (MHz) (mA)	C _{CB} / V _{CB} typ (pF) (V)	G _{pe} G _{pb} * typ (dB)	F / I _C / f typ (dB) (mA) (MHz)					
BF 167	N	AGC IF TV amplifier <i>Ampli. CAG FI TV</i>	150	30	400	4	0,15	10	42	3	4	36	 TO 72
BF 173	N	TV IF amplifier <i>Ampli FI TV</i>	230	25	600	7	0,23	10	43		7	36	
BF 182	N	VHF mixer oscillator <i>Oscillateur-mélangeur VHF</i>	150	20	700	2	0,3	10	12*		2	800	 TO 72
BF 272 A	P	UHF AGC amplifier <i>Ampli CAG UHF</i>	200	35	850	3	0,3	10	15*	3,7	3	800	
BF198	N	AGC TV IF amplifier <i>Ampli FI CAG TV</i>	300	30	400	4	0,25	10	42	3	4	36	 CB-76
BF199	N	TV IF amplifier <i>Ampli FI TV</i>	300	25	550	7	0,32	10	43		7	36	
ESM 791	N	SAW TV IF preamplifier <i>Préampli FI TV FOS</i>	400	20(1)	5000	30	0,7	5	24	3,5	30	200	
BF 240	N	FM IF amplifier <i>Ampli FI FM</i>	300	40	430	1	0,27	10		1,5	1	0,2	
BF 241	N		300	40	400	1	0,27	10		1,5	1	0,2	
BF 253	N	AM IF amplifier <i>Ampli FI AM</i>	300	30	280	1	0,7	10		1,2	1	1	
BF 254	N		300	30	300	1	0,7	10		1,2	1	1	
BF 255	N	FM amplifier, mixer <i>mélangeur, ampli FM</i>	300	30	250	1	0,7	10		4	1	100	
BF 502 S	N	VHF mixer, oscillator <i>Oscillateur mélang. VHF</i>	400	25	900	5	0,32	10	22		20	200	
ESM 282	N		300	30	900	5	0,38	10	21		5	200	
BF 506	P		250	35	700	3	0,7	10	18*	2,5	3	200	
BF 509 T	P	AGC VHF amplifier <i>Ampli CAG VHF</i>	250	35	700	3	0,65	10	17*	2	3	200	 TO 92
BF 679	P	AGC UHF amplifier <i>Ampli CAG UHF</i>	170	35	850	3	0,45	10	13*	3,7	3	800	

(1) V_{CER}